## SAVOX

## SAVOX NOISE-COM 400 Ex Motorola ANC RSM

This version of SAVOX® Noise-COM 400 Ex is compatible with Ex-approved Motorola PMMN4093 and PMMN4094 ACN remote speaker microphones. Comes with dynamic boom microphone.

## Key Benefits:

- · Protects hearing (SNR 30 dB) · Ex approved can be used in potentially explosive environments like oil rigs
- · Replaceable mic and ear cushions
- $\cdot$  Mounts easily into construction helmets (list of certified helmets from Sales)
- · Durable design



Market Segment	Personal Safety
Housing Material	ABS
Weight (text)	375 g

Operational Temperature Min	-20 °C (-4 °F)
Storage Temperature Min	-20 °C (-4 °F)
Protection Against Drop(fall)	2 meters
Headset Connector	QR4 male
Cable Type	Coiled
Hearing Protector Certification	EN 352, US
Attachment/Fastening	Helmet mount

Product code Housing Colour Options (text)

Operational Temperature Max Storage Temperature Max Microphone Type Connectivity Ex/IS Emergency Button

Hearing Protector Attenuation

K53692-3500

Blue

Helmet specific adapters for most common helmets<br/>br/>When ordering, please inform the correct helmet model to be used with the headset

55 °C (131 °F) 60 °C (140 °F) Dynamic Wired ATEX/IECEX

No

SNR 30dB, according to EN352-3:2002<br/>br/>NRR 24dB, according to ANSI S3.19-1974